


HOW TO PRINT PARAMETER SETTINGS USING A MODEL 7000E

STEP 1: Removing Top Cover

Unlock cover. Hold the left and right sides of the cover and lift up.





STEP 2:

Activating "Parameter Print" Mode


Step 2 (illustration)

Press and hold the right control button (4th), and press reset switch simultaneously while holding down right control button. Display goes blank.

Release Reset button first then release right-side button. Display will show (1P) and (1).

STEP 3: Print Time Card

Insert time card. The clock will print parameters on time card as shown on right..



STEP 4:

Exit "Parameter Print" Mode

Press and release Reset Switch (see illustration in step 2 for location of Reset Switch). Normal operation will resume.

STEP 5: Replacing Top Cover

Fit the plugs on both sides of cover into the holes located on the unit of the body. Then push down while pulling the cover slightly forward.



Hours Ra		te		Amount	
START			ACCUMULATED		
IN	OUT	HOURS	TOTAL	COMMENTS	
QR-375la93	informat	ion Pl	/5		
2001/02/21	04:53	000293			
Pay Period	5 - 1				
Print Forma	t 2 - 2	- 2			
Round 1 -	1				
Auto Break	08:30 -	60			
MAX IN 1	- 13				
Button Fund	tion 2				
DST b:'01/0	4/01 e:'0	1/10/2	B		
Language	1				
000101:24:0	0:00:00	00:00			
010127:23:5	9:00/010	218:03:	31:08		
		<u> </u> В:	= Automatic	Break Deduction	
l		_			

001